

MAX96700

14-Bit GMSL Deserializer with Coax or STP Cable Input

Compact 1.6Gbps Deserializer with Eye-Width Monitor and CRC Protection of Video and Control Data for ADAS Applications

Description

The MAX96700 is a compact deserializer especially suited for automotive camera applications. Features include adaptive equalization and an output crosspoint switch. An embedded control channel operates at 9.6kbps to 1Mbps in UART, I²C, and mixed UART/I²C modes, allowing programming of serializer, deserializer (SerDes), and camera registers, independent of video timing.

The deserializer can track data from a spread-spectrum serial input. The serial input meets ISO 10605 and IEC 61000-4-2 ESD standards. The core supply range is 1.7V to 1.9V and the I/O supply range is 1.7V to 3.6V. The device is available in a 32-pin (5mm × 5mm) TQFN package with 0.5mm lead pitch, and operates over the -40°C to +115°C temperature range.

Key Features

- Ideal for Safety Camera Applications
 - Works with Low-Cost 50Ω Coax (100Ω STP) Cables
 - Error Detection of Video/Control Data
 - High-Immunity Mode for Robust Control-Channel EMC Tolerance
 - Retransmission of Control Data Upon Error
 - Best-in-Class Supply Current: 190mA (max)
 - Adaptive Equalization for 15m Cable at Full Speed
 - 32-Pin (5mm × 5mm) TQFN Package
 - Horizontal- and Vertical-Sync Encoding and Tracking
- High-Speed Deserialization for Megapixel Cameras
 - Up to 1.74Gbps Serial-Bit Rate
 - 6.25MHz to 87MHz ×12-Bit + H/V Data
 - 36.66MHz to 116MHz ×12-Bit + H/V Data (through Internal Encoding)
- Multiple Modes for System Flexibility

- 9.6kbps to 1Mbps Control Channel in UART, I²C (with Clock Stretch), or UART-to-I²C Modes
- 2:1 Input Mux for Camera Selection
- 15 Hardware-Selectable I²C-Device Addresses
- Pairs with Any Maxim GMSL Serializer
- Crosspoint Switch Maps Data to any Output
- Reduces EMI and Shielding Requirements
 - Spread-Spectrum Serial-Input Tracking and Transfer to the Parallel Output
 - 1.7V to 1.9V Core and 1.7V to 3.6V I/O Supply
- Peripheral Features for System Verification
 - Built-In PRBS Receiver for BER Testing
 - Eye-Width Monitor Allows In-System Test of High-Speed Serial Link
 - Dedicated “Up/Down” GPI for Camera Frame Sync Trigger and Other Uses
- Meets AEC-Q100 Automotive Specification
 - -40°C to +115°C Operating Temperature Range
 - ±8kV Contact and ±15kV Air IEC 61000-4-2 and ISO 10605 ESD Protection

Applications/Uses

- Automotive Camera Applications

Part Number	Signal Type	Signal Type	Functions	Rx	Tx	Data Rates (Mbps)	V _{SUPPLY} (V)	Package/Pins
	Rx	Tx						
MAX96700	CML	CMOS	Deserializer	1	14	1500	1.8	TQFN/32
		LVC MOS					3.3	