



1795 MHz Cavity Band Pass Filter

Part Number: AE1795B10862



ANATECH ELECTRONICS INC
RF & Microwave Filters & Products

Electrical Specifications

- Center Frequency: 1795 MHz
- Bandwidth: 170 MHz
- Passband: 1710-1880 MHz
- Insertion Loss: 1 dB Max
- Return Loss: 15 dB Min
- Rejection: 30 dB @ 1660 MHz
30 dB @ 1930 MHz
- Power Handling: 150 Watts Max


Mechanical

- Connector Type: SMA (F)
- Dimensions: 7.33 x 1.879 x 1.0 Inches

Environmental

- Operating Temperature: -40 to +80° C

Outline Drawing:





1795 MHz Cavity Band Pass Filter



ANATECH ELECTRONICS INC
RF & Microwave Filters & Products

Part Number: AE1795B10862

Response Plot:

21 Feb 2012 10:21:43
 CH1 S₁₁ log MAG 5 dB/ REF 0 dB 3: -15.492 dB
 CH2 S₂₁ log MAG 5 dB/ REF 0 dB 1: -.2577 dB

