



9000-10600 MHz Bandpass Filter

Part Number: AE9800B10626

Passband:	9000-10600 MHz
Frequency:	9800 MHz
Insertion Loss:	1.7 dB max.
VSWR:	1.7:1
3.0 dB @ Relative BW Lower Limit:	9860 MHz Max
3.0 dB @ Relative BW Upper Limit:	10140 MHz Min
Attenuation:	20 dB @ 8900 MHz 40 dB @ 8800 MHz 20 dB @ 10700 MHz 40 dB @ 10800 MHz
Impedance:	50 Ohms

Outline Drawing:

