



Notch Filter

Part Number: AS840N339

Passband Frequency:	695 to 825MHz 850 to 2000MHz
Passband Insertion Loss:	695 to 825MHz @ 1 dB 850 to 2000MHz @ 1dB
Passband Return Loss:	14 dB min
Channel rejection	70 dB min @ 840 - 841 MHz >30dB @ 839 MHz >30dB @ 842 MHz
Connectors:	N Female
Temperature Range:	0 to 120 deg. C
Mounting	Mounting tabs with 8-32 clearance holes
Size:	17.2" x 2.2" x 3.2"

Outline Drawing:

